

SA312



Brand: AUDIOCENTER
Product Code: 0111
Availability: In Stock
Weight: 48.50lb
Dimensions: 18.03in x 17.40in x 27.67in

Price: \$765.00

Description

Two combo inputs CH A (1-way XLR and Mono jack 6.35) are available in SA312, which can be switched between line input and microphone input. The audio port CH B (Mono jack 6.35 or a RCA port) is for the other sound resources like MP3, CD player, etc. There is 1-way signal input port for wireless bluetooth in it and the volume is controlled by terminal. The gain of CH A/CH B signal input is controlled by independent knob and 1-way master volume control knob. The four different audio sources can be parallel output with one-way XLR after mixed internally, and then sent to different speakers for sound distribution.

SA312 can be installed by steel wire. It can also be ground standing by coupling bar or three-feet stand. The pole mount is 35mm. Various accessories are offered for SA312 to meet different kinds of installs.

Product Gallery



JBL
 Dynamic Audio Systems

SA312



Technical specifications

For more information, please visit our website at www.jbl.com.
 © 2012 JBL, Inc. All rights reserved. JBL, the JBL logo, and SA312 are trademarks of JBL, Inc. in the USA and other countries. Other trademarks are the property of their respective owners.

SA312	
Type	Active 2-way powered speaker
Frequency Response	50 Hz - 20 kHz
Impedance	16 Ω
Max Power	1000 W (1000 W RMS)
Max SPL	120 dB (1 m, 1 kHz)
Dimensions	180 x 180 x 180 mm (7.1 x 7.1 x 7.1 in.)
Weight	1.8 kg (4.0 lb)
Features	• 16 Ω impedance • 1000 W max power • 120 dB max SPL • 50 Hz - 20 kHz frequency response • 180 x 180 x 180 mm dimensions • 1.8 kg weight



JBL
 Dynamic Audio Systems

