

SA312



Brand: AUDIOCENTER

Product Code: 0111

Availability: In Stock

Weight: 48.50lb

Dimensions: 18.03in x 17.40in x 27.67in


Price: \$695.00

Description

Two combo inputs CH A (1-way XLR and Mono jack 6.35) are available in SA312, which can be switched between line input and microphone input. The audio port CH B (Mono jack 6.35 or a RCA port) is for the other sound resources like MP3, CD player, etc. There is 1-way signal input port for wireless bluetooth in it and the volume is controlled by terminal. The gain of CH A/CH B signal input is controlled by independent knob and 1-way master volume control knob. The four different audio sources can be parallel output with one-way XLR after mixed internally, and then sent to different speakers for sound distribution.

SA312 can be installed by steel wire. It can also be ground standing by coupling bar or three-feet stand. The pole mount is 35mm. Various accessories are offered for SA312 to meet different kinds of installs.

Product Gallery



JBL
 Professional Audio

SA312



Technical specifications:
 Frequency response: 40 Hz - 20 kHz
 Power handling: 1000 W (1 kHz, 1% THD)
 Impedance: 16 Ω
 Dimensions: 400 x 300 x 150 mm
 Weight: 10 kg

SA312	
Type	Two-way active speaker
Frequency response	40 Hz - 20 kHz
Power handling	1000 W (1 kHz, 1% THD)
Impedance	16 Ω
Dimensions (H x W x D)	400 x 300 x 150 mm
Weight	10 kg
Features	<ul style="list-style-type: none"> Two-way active speaker 16 Ω impedance 1000 W power handling 40 Hz - 20 kHz frequency response 400 x 300 x 150 mm dimensions 10 kg weight



JBL
 Professional Audio

