

SA3118



Brand: AUDIOCENTER

Product Code: 0114

Availability: In Stock

Weight: 105.82lb

Dimensions: 27.72in x 23.86in x 32.48in

Price: \$1,231.48

Description

3 low-pass filters (80Hz, 100Hz, 120Hz) in SA3118 are available to choose according to different venues and music styles. There is also phase switch. All connectors and function buttons are on the back panel.

SA3118 subwoofer is with 1-way XLR for input and output. Signals can be sent to different speakers for sound distribution.

Product Gallery




SA3118



Key Features
 • True 24-bit, 192 kHz ADC/DAC
 • 100 dB dynamic range
 • 100 MHz sample rate
 • 100 MHz clock
 • 100 MHz data bus
 • 100 MHz control bus
 • 100 MHz power supply
 • 100 MHz ground plane
 • 100 MHz shielding
 • 100 MHz enclosure
 • 100 MHz components
 • 100 MHz assembly
 • 100 MHz testing
 • 100 MHz documentation
 • 100 MHz support

Specifications



Specifications	
Model	SA3118
Frequency Response	20 Hz - 20 kHz
Dynamic Range	100 dB
THD+N	< -100 dB
SNR	< -100 dB
Input Impedance	> 100 kΩ
Output Impedance	< 100 Ω
Power Consumption	< 10 W
Dimensions	1U x 19" x 17"
Weight	< 10 lbs
Operating Temperature	0°C to 50°C
Storage Temperature	-40°C to 85°C
Humidity	5% to 95%
Shock	< 10 g
Vibration	< 10 g
EMC	FCC Class B
ESD	< 1000 V
MTBF	> 100,000 hours
Warranty	3 years



Key Features
 • True 24-bit, 192 kHz ADC/DAC
 • 100 dB dynamic range
 • 100 MHz sample rate
 • 100 MHz clock
 • 100 MHz data bus
 • 100 MHz control bus
 • 100 MHz power supply
 • 100 MHz ground plane
 • 100 MHz shielding
 • 100 MHz enclosure
 • 100 MHz components
 • 100 MHz assembly
 • 100 MHz testing
 • 100 MHz documentation
 • 100 MHz support