beyma

PROFESSIONAL LOUDSPEAKERS
www.beyma.com

15LEX1200Nd

LOW FREQUENCY TRANSDUCER

Preliminary Data Sheet

KEY FEATURES

maltcross TECHNOLOGY

- High power handling and low distortion 15” subwoofer
- Exclusive Malt Cross® Technology Cooling System
- Low power compression losses
- High sensitivity: 97 dB (1W / 1m)
- FEA optimized neodymium magnetic circuit
- Ultra low air noise
- Optimized linear behaviour
- Weatherproof cone with treatment for both sides
- 4” DUO double layer in/out copper voice coil
- Extended controlled displacement: X_{max} ± 11 mm
- 60 mm peak-to-peak excursion before damage
- Optimized for direct radiation and band-pass subwoofer applications

TECHNICAL SPECIFICATIONS

Nominal diameter	380 mm	15 in
Rated impedance		8 Ω
Minimum impedance		5,8 Ω
Power capacity [1]		1.200 W_{AES}
Program power [2]		2.400 W
Sensitivity	97 dB	1W / 1m @ Z_N
Frequency range		40 - 1.500 Hz
Recom. enclosure		V_b = 115 l
(Bass-reflex design)		F_b = 40 Hz
Voice coil diameter	101,6 mm	4 in
Bl factor		26,4 N/A
Moving mass		164 g
Voice coil length		28 mm
Air gap height		14 mm
X_{damage} (peak to peak)		60 mm

THIELE-SMALL PARAMETERS [3]

Resonant frequency, f_s	36 Hz
D.C. Voice coil resistance, R_e	5,1 Ω
Mechanical Quality Factor, Q_{ms}	6,2
Electrical Quality Factor, Q_{es}	0,32
Total Quality Factor, Q_{ts}	0,30
Equivalent Air Volume to C_{ms}, V_{as}	127 l
Mechanical Compliance, C_{ms}	0,115 mm / N
Mechanical Resistance, R_{ms}	6,1 kg / s
Efficiency, η_0	1,86 %
Effective Surface Area, S_d	0,088 m^2
Maximum Displacement, X_{max} [4]	11 mm
Displacement Volume, V_d	0.97 l
Voice Coil Inductance, L_e	1,5 mH

Notes:

[1] The power capaticty is determined according to AES2-1984 (r2003) standard.

[2] Program power is defined as power capacity + 3 dB.

[3] T-S parameters are measured after an exercise period using a preconditioning power test. The measurements are carried out with a velocity-current laser transducer and will reflect the long term parameters (once the loudspeaker has been working for a short period of time).

[4] The X_{max} is calculated as $(L_{vc} - H_{ag})/2 + (H_{ag}/3,5)$, where L_{vc} is the voice coil length and H_{ag} is the air gap height.

Acústica Beyma SL - P.I. Moncada II, C/ Pont Sec, 1C - 46113 Moncada, Valencia (Spain) - Tel. +34 96 130 13 75 - beyma@beyma.com

beyma

PROFESSIONAL LOUDSPEAKERS

www.beyma.com

15LEX1200Nd

LOW FREQUENCY TRANSDUCER

Preliminary Data Sheet



Note: Frequency response measured with loudspeaker standing on infinite baffle in anechoic chamber, 1W @ 1m

MOUNTING INFORMATION

Overall diameter	393 mm	15,5 in
Bolt circle diameter	373 mm	14,7 in
Baffle cutout diameter:		
- Front mount	352 mm	13,9 in
Depth	183 mm	7,2 in
Volume displaced by driver	4,5 l	0,16 ft³
Net weight	8,4 kg	18,5 lb
Shipping weight	8,6 kg	18.9 lb

DIMENSION DRAWING